



型號 Auto switch model




LM- 43VS (L 型 / 具過載保護)



電線方向	Electrical entry direction	180°
出線方式	Wiring type	2 - wire
輸出方式	Output type	N,O (Normally open)
適用負載	Applicable load	24 VDC Relay , PLC
輸入電壓	Power supply voltage	/
消耗電流	Current consumption	/
負載電壓	Load voltage	24 VDC (10 to 26.5 VDC)
負載電流	Load current	50 mA
內部壓降	Internal voltage drop	≤ 4.5 V
洩漏電流	Leakage current	≤ 0.2 mA 【24VDC】
指 示 灯	Indicator light	Red LED
周圍溫度	Ambient temperature	-5 ~ 60°C
依據標準	Standard	UL , CE

● 線長	Wire length	誤差	Tolerance	重量	Weight
	1M		± 30 mm		
	2M		± 60 mm		
	3M		± 90 mm		
	5M		± 150 mm		



保護裝置 Protection circuit

電源電壓反接	Power supply voltage reversal	Yes	No
突波電壓保護	Transient voltage protection	Yes	No
過電流保護 (瞬間電流) ≤ 2000mA	Overcurrent protection (surge current) ≤ 2000mA	Yes	No
短路保護	Short circuit protection	Yes	No

● 2 線式串接，作動時輸出負載電壓：24V – 4.5V x 2 pcs = 15V

2-wire with 2-switch AND connection :

Load voltage at ON = Power supply voltage – Residual voltage x 2 pcs = 24V – 4.5V x 2 pcs = 15V

● 2 線式並接，不作動時負載電壓：1 mA x 2 pcs x 3 KΩ = 6 V

2-wire with 2-switch OR connection :

Load voltage at OFF = Leakage current x 2 pcs x Load impedance = 1 mA x 2 pcs x 3 KΩ = 6 V